

HVA 1000.2

HVA 1500.2



Amplificatore 2 canali in Classe D.
 Uscite in impedenza 2/4/8 ohm o a tensione costante 70v e 100v,
 ingombro 1 unità rack.
 Conessioni: XLR in – Speakon out

HVA1000.2

Power Stereo Mode (Both Channels Driven) 2 Ohms (EIAJ): 2000W x 2 / 4 Ohms (RMS): 900W x 2 / 8 Ohms (RMS): 600 x 2
 Bridge Mono Mode 8 Ohms (RMS): 1800W / 4 Ohms (EIAJ): 4000W
 Voltage Gain (100V) 37 (+/-0.5dB)
 Misure: 483 x 360 x 44 mm
 Weight: 5,7kg.

HVA1500.2

Power Stereo Mode (Both Channels Driven) 2 Ohms (EIAJ): 2800W x 2 / 4 Ohms (RMS): 1500W x 2 / 8 Ohms (RMS): 900 x 2
 Bridge Mono Mode 8 Ohms (RMS): 1000W / 4 Ohms (EIAJ): 1800W
 Voltage Gain (100V) 38 (+/-0.5dB)
 Misure 483 x 446 x 44 mm
 Weight 6,1kg.

Input Sensitivity (Limiter Off) 0.9 – 1.1V (+/-1dBv)
 Input Impedance 20KΩ balanced or 10KΩ unbalanced
 Frequency Response 20Hz~20KHz (+0/-1dB) (At 10dB Below Output Power 8Ω)
 THD + N <0.1% (Ref. 1KHz 1/8 Rated Power, A-Weighted)
 S/N Ratio >100dB (Ref. Rated Power, A-Weighted)
 Crosstalk (Below Rated Power) >70dB
 Damping Factor (1KHz, 8W) >200
 Power/Output Circuitry Switching Power Class-D

