



Freedom H1

Freedom H1 is a compact 100% TRUE wireless, battery-operated, LED wash light with a built-in D-Fi transceiver. The fixture features a single hex-color (RGBAW+UV) 10W LED. Its magnetic base makes it easy to mount the light to most metal surfaces providing added versatility. Because of its small size, Freedom H1 features effortless transport and set-up. Freedom H1 has a digital display for easy control and adjustment of all settings. Multiple control options include stand-alone mode, wireless DMX, or IR. The Freedom H1 X4 system includes 4 fixtures, 4 diffusers, a carry bag, multi-charger, and [IRC-6 remote](#).



Highlights

- 100% TRUE wireless, battery-operated, LED wash with built-in D-Fi transceiver
- System includes 4 fixtures, 4 diffusers, a carry bag, multi-charger and [IRC-6](#) remote
- Quick swapping of filters and gradients with the included magnetic gel holder
- Multiple control options include stand-alone, wireless DMX or IR
- Compact size provides effortless transport and set-up
- Digital display for easy control and adjusting all settings
- Magnetic base to easily mount light to most metal surfaces
- Built-in Kensington security slot prevents theft

Specifications

- DMX Channels: 6, 8 or 12
- Light Source: 1 LED (hex-color RGBAW+UV) 10W, (3 A), 50,000 hours life expectancy
- Strobe Rate: 0 to 25 Hz
- Beam Angle: 21°
- Field Angle: 32°
- Operating Frequency: 2.412 to 2.484 GHz
- Illuminance: (w/ filter): 268 lux @ 2 m
(w/o filter): 314 lux @ 2 m
- Input Voltage: 8.4VDC, 1.5A (external power supply: 100-240 VAC, 50/60 Hz)
- Weight: 1.4 lb (0.7 kg)
- Size: 3.8 x 3 x 8.5 in (97 x 75 x 139 mm)
- Approvals: CE, FCC
- Maximum Run Time (all on): up to 8 hours
- Maximum Run Time (single color): up to 20 hours
- Recharge Time: 7 hours
- Bracket Mounting Hole: M12

What's Included

- 4x Freedom H1
- 4x diffusers
- Multi charger
- Freedom H1
- Carry bag