

SMARTBCON192



WIRELESS CONTROL DESK W-DMX

The SMARTBCON192 control table is a wireless solution from Sweden that is compliant with the DMX512/1990 standard. It features 12 smart controls that can control up to 16 channels for a total of 192 channels. It also has 23 banks, each with 8 scenes, and 6 chases, each with up to 184 scenes. Additionally, it has the capability to record up to 6 chases with time and fade speeds. The table also has 16 faders for direct channel control and MIDI control over banks, chases, and blackout. Additionally, it has a built-in microphone for music mode and a "blackout" feature. The table also comes with a digital LED cabinet that has 1-chases, 2 scenes, 3 and 4 banks, and an auto mode program controlled by fade time sliders. The DMX In/Out connection is a 3-pin XRL and it comes in an elegant and durable casing.



Battery
Powered



Multiple
Channels



Wireless
DMX

Parameters and technical information

Control protocol	DMX512 / 1990 standard.	Finish	Elegant and durable casing.
DMX Channels	12 Smart controls up to 16 channels, 192 channels in total.	Dimensions	482 x 133 x 82 mm.
Programming	23 banks, each with 8 scenes; 6 Chases, each with up to 184 scenes.	Weight	2.0 kg.
Show record	Recording of up to 6 Chases with time and fade speeds.	Operating range	DC 9V-12V 500mA min
Faders	16 faders for direct channel control.	Maximum ambient temperature	45 ° C.
Function mode	Built-in microphone for music mode.	Data Input	Locking 3-pin male XLR plug.
Display	Digital LED Cabinet 4. 1- Chases, 2 scenes, 3 and 4 banks.	Data Output	Locking 3-pin XLR female connector.
Control modes	Auto mode program controlled by fade time sliders. MIDI control over banks, chases and blackout.	Dimensions (LxWxH)	145 x 100 x 57 mm
DMX In/Out	3-pin XRL	Weight	1,2 kg
		Certification	CE